

REPORT ON ELECTRIC LIGHTING INSTALLATION. No. 2478

Port of Rohe Date of First Survey 6 Febry Date of Last Survey 10 Mar. 1919 No. of Visits 9
 No. in Reg. Book on the ~~Non~~ Steel Sea Strut "Washington" Mem Port belonging to Rohe
 Built at The Kawasari Dryd Co Ltd By whom The Kawasari Dryd Co Ltd When built 1919
 Owners The Kawasari Dryd Co Ltd Owners' Address _____
 Yard No. 496 Electric Light Installation fitted by The Kawasari Dryd Co Ltd When fitted 1919

DESCRIPTION OF DYNAMO, ENGINE, ETC.

Two sets of compound dynamo coupled directly to the single cylinder automatic cut off vertical enclosed engine with forced lubrication. 8" dia., 6" stroke 450 R.P.M.

Capacity of Dynamo 170 Amperes at 100 Volts, whether continuous or alternating current continuous

Where is Dynamo fixed In the engine room.

Position of Main Switch Board in the engine room having switches to groups A, B, C, D, E + etc. of lights, &c., as below

Positions of auxiliary switch boards and numbers of switches on each 2 in the engine room, 4 on the shelter deck, 1 on the lower bridge and 1 on the after main having one main switch on each board.

If cut outs are fitted on main switch board to the cables of main circuit yes and on each auxiliary switch board to the cables of auxiliary circuits yes and at each position where a cable is branched or reduced in size yes and to each lamp circuit yes

If vessel is wired on the double wire system are cut outs fitted to both flow and return wires or cables of all circuits including lamp circuits yes.

Are the cut outs of non-oxidizable metal yes and constructed to fuse at an excess of 100 per cent over the normal current

Are all cut outs fitted in easily accessible positions yes. Are the fuses of standard dimensions yes. If wire fuses are used are permanent instructions fitted on or near each switch board giving particulars of proper size of fuse for each circuit yes

Are all switches and cut-outs constructed of incombustible materials and fitted on incombustible bases yes, porcelain + marble are used.

Total number of lights provided for 163 lamps arranged in the following groups:—

A	<u>116 incandescent</u> lights each of <u>16</u> candle power requiring a total current of <u>52.0</u> Amperes
B	<u>13 incandescent</u> lights each of <u>5</u> candle power requiring a total current of <u>2.5</u> Amperes
C	<u>32 incandescent</u> lights each of <u>32</u> candle power requiring a total current of <u>36.0</u> Amperes
D	<u>2 arc</u> lights each of <u>1,200</u> candle power requiring a total current of <u>9.0</u> Amperes
E	lights each of _____ candle power requiring a total current of _____ Amperes
	<u>2 Mast head light with 2 lamps each of 32</u> candle power requiring a total current of <u>2.24</u> Amperes
	<u>2 Side light with 2 lamps each of 32</u> candle power requiring a total current of <u>2.24</u> Amperes
	Cargo lights of _____ candle power, whether incandescent or arc lights.

If arc lights, what protection is provided against fire, sparks, &c.

Where are the switches controlling the masthead and side lights placed.

DESCRIPTION OF CABLES.

Main cable carrying 170.0 Amperes, comprised of 1636 wires, each No. 30 L.S.G. diameter, 0.01970 square inches total sectional area
 Branch cables carrying 27.0 Amperes, comprised of 11 wires, each No. 20 L.S.G. diameter, 0.0110 square inches total sectional area
 Branch cables carrying 18.5 Amperes, comprised of 19 wires, each No. 20 L.S.G. diameter, 0.0190 square inches total sectional area
 Branch cables carrying 14.0 Amperes, comprised of 2 wires, each No. 16 L.S.G. diameter, 0.0064 square inches total sectional area
 Branch cables carrying 15.5 Amperes, comprised of 2 wires, each No. 16 L.S.G. diameter, 0.0064 square inches total sectional area
 Branch cables carrying 24.5 Amperes, comprised of 14 wires, each No. 20 L.S.G. diameter, 0.0140 square inches total sectional area
 Leads to lamps carrying 0.5 Amperes, comprised of 1 wires, each No. 18 L.S.G. diameter, 0.0018 square inches total sectional area

Cargo light cables carrying 4.5 Amperes, comprised of 283 wires, each No. 38 L.S.G. diameter, 0.0080 square inches total sectional area

DESCRIPTION OF INSULATION, PROTECTION, ETC.

Conductors are doubly insulated with india rubber and vulcanized rubber and tape.

Cables are protected against mechanical injury and chemical action by steel armor-ing or lead covering according to the requirements.

Joints in cables, how made, insulated, and protected Mechanical joints are made throughout and protected with water-tight cast iron boxes.

Are all the joints of cables thoroughly soldered, resin only having been used as a flux yes. Are all joints in accessible positions, none being made in bunkers, cargo spaces, or spaces which may at any time be used for carrying cargo, stores, or baggage yes

Are there any joints in or branches from the cable leading from dynamo to main switch board None

How are the cables led through the ship, and how protected Cables are led unconcealed and without any additional protection those on cables themselves.

DESCRIPTION OF INSULATION, PROTECTION, ETC.—continued.

Are they in places always accessible *They are all in accessible places.*

What special protection has been provided for the cables in open alleyways or where exposed to weather or moisture *Without any additional protections beside those on the cables themselves.*

What special protection has been provided for the cables near galley, or oil lamps or other sources of heat *as before*

What special protection has been provided for the cables near boiler casings *as before*

What special protection has been provided for the cables in engine room *In some parts where necessary the cables are led through iron pipe.*

How are cables carried through beams *Pierced through & wood lined* through bulkheads, &c. *Pierced through & provided with water-tight glands.*

How are cables carried through decks *Pierced and led through iron pipes.*

Are any cables run through coal bunkers *Yes* or cargo spaces *Yes* or spaces which may be used for carrying cargo, stores, or baggage *Yes.*

If so, how are they protected *With lead covering and steel armoring on the cables themselves.*

Are any lamps fitted in coal bunkers or spaces which may at times be used for cargo, coals, or baggage *None*

If so, how are the lamp fittings and cable terminals specially protected

Where are the main switches and cut outs for these lights fitted

If in the spaces, how are they specially protected

Are any switches or cut outs fitted in bunkers *None*

Cargo light cables, whether portable or permanently fixed *portable* How fixed *in the water-tight cast iron boxes.*

In vessels fitted on the single wire system, how is the dynamo terminal fixed to the hull of vessel

How are the returns from the lamps connected to the hull

Are all the joints with the hull in accessible positions

VESSELS BUILT FOR CARRYING PETROLEUM.

In vessels built for carrying petroleum, are all switches and cut-outs fitted in positions not liable to the accumulation of petroleum vapour or gas

Are any switches, cut outs, or joints of cables fitted in the pump room or companion

How are the lamps specially protected in places liable to the accumulation of vapour or gas

The installation is supplied with a voltmeter and *two* ~~an~~ *amperometers*, fixed *on a marble switch board.*

The copper used is guaranteed to have a conductivity of *98* per cent. that of pure copper.

Insulation of cables is guaranteed to have a resistance of not less than *600* megohms per statute mile after 24 hours' immersion in seawater.

The foregoing statements are a correct description of the Electric Light installation fitted by us on this vessel and we declare that it is at this date in good order and safe working condition.

Mura Electrical Engineers Date *11-4-19*

COMPASSES.

Distance between dynamo or electric motors and standard compass	<i>Dynamo to standard compass</i>	<i>115 feet</i>
	<i>Motor " " "</i>	<i>110 feet</i>
Distance between dynamo or electric motors and steering compass	<i>Dynamo " steering "</i>	<i>105 feet</i>
	<i>Motor " " "</i>	<i>100 feet</i>

The nearest cables to the compasses are as follows:—

A cable carrying	<i>5.6</i> Amperes	<i>6</i> feet from standard compass	<i>15</i> feet from steering compass
A cable carrying	<i>13.5</i> Amperes	<i>17</i> feet from standard compass	<i>13</i> feet from steering compass
A cable carrying	Amperes	feet from standard compass	feet from steering compass

Have the compasses been adjusted with and without the electric installation at work at full power

The maximum deviation due to electric currents, etc., was found to be _____ degrees on _____ course in the case of the standard compass and _____ degrees on _____ course in the case of the steering compass.

Kawasaki *J. Otake* Builder's Signature. Date _____
Per _____ Secretary.

GENERAL REMARKS.

The installation has been fitted in accordance with the Rule requirements & worked satisfactorily on trial.

It is submitted that this vessel is eligible for THE RECORD. ELEC. LIGHT. *J.W.D. Rell 6-6-19.*

Surveyor to Lloyd's Register of British and Foreign Shipping.

Committee's Minute *FRI. 6-JUN. 1919*



THE SURVEYORS ARE REQUESTED NOT TO WRITE ACROSS THIS MARGIN.

REPORT FORM NO. 13.