

REPORT ON ELECTRIC FITTINGS.

(OTHER THAN FOR THE PROPULSION OF THE VESSEL)

14 APR 1931

Date of writing Report 9th April 1931 When handed in at Local Office 11th April 1931 Port of Gothenburg Received at London OfficeNo. in Survey held at Gothenburg Date, First Survey 13th Feb Last Survey 30th March 1931
Reg. Book. 92484 on the Steel Twin Screw Motorship "SKOTAAS" (Number of Visits 8)Tons { Gross 8190
Net 4894

Built at Dundee By whom built Caledon S.P. & Eng. Co. Yard No. 335 When built 1931

Owners Skibs A/S Nanset Port belonging to Larvik

Electric Light Installation fitted by A.-B. Götaverken Contract No. 452 When fitted 1931

Is the Vessel fitted for carrying Petroleum in bulk Yes.

System of Distribution Two wire system.

Pressure of supply for Lighting 110 volts, Heating - volts, Power 110 volts.

Direct or Alternating Current, Lighting Direct Power

If alternating current system, state frequency of periods per second -

Has the Automatic Governor been tested and found efficient when the whole load is suddenly thrown on or off Yes.

Generators, do they comply with the requirements regarding rating Yes., are they compound wound Yes.

are they over compounded 5 per cent. Yes, if not compound wound state distance between each generator -

Where more than one generator is fitted are they arranged to run in parallel Yes, is an adjustable regulating resistance fitted in

series with each shunt field Yes.

Are all terminals accessible, clearly marked, and furnished with sockets Yes, are they so spaced or shielded that they cannot be accidentally earthed,

short circuited, or touched Yes Are the lubricating arrangements of the generators as per Rule Yes

Position of Generators On a platform aft in the motorroom,

is the ventilation in way of the generators satisfactory Yes, are they clear of all inflammable material Yes

if situated near unprotected woodwork or other combustible material, state distance of same horizontally from or vertically above the generators

- and -, are the generators protected from mechanical injury and damage from water, steam or oil Yes

are their axes of rotation fore and aft Yes

Earthing, are the bedplates and frames of the generating plant efficiently earthed Yes are the prime movers and

their respective generators in metallic contact Yes

Main Switch Boards, where placed on the same platform as the generators

If the generators and main switchboard are not placed in the same compartment, is each generator provided with

a fuse on each insulated pole as near as possible to the terminals of the generator, additional to that provided on the main switchboard -

Switchboards, are they placed in accessible positions, free from inflammable gases and acid fumes Yes

are they protected from mechanical injury and damage from water, steam or oil Yes, if situated near unprotected

woodwork or other combustible material, state distance of same horizontally from or vertically above the switchboards - and -

are they constructed wholly of durable, non-ignitable non-absorbent materials of marble, is all insulation of high dielectric strength and of

permanently high insulation resistance Yes, if semi-insulating material is used, are all conducting parts insulated from the slab

with mica or micanite or other non-hygroscopic insulating material, and the slab similarly insulated from its framework Yes

and is the frame effectively earthed Yes Are the fittings as per Rule regarding:— spacing or shielding of live parts

Yes, accessibility of all parts Yes, absence of fuses on back of board Yes, proportion of omnibus

bars Yes, individual fuses to voltmeter, pilot or earth lamp Yes, connections of switches Yes

Main Switchgear, description of switchgear for each generator and each outgoing circuit, and arrangement of equalizer switches for each generator

A double pole circuit-breaker with overload and reversed current trips and a single pole

equalizer switch. For each outgoing circuit: A double pole linked switch and a fuse at each pole.

Instruments on main switchboard 3 ammeters 2 voltmeters - synchronising device for paralleling purposes.

Earth Testing, state what means are provided at the main switchboard for indicating the state of the insulation of the system ohm meter fitted

with commutator for both poles.

Switches, Circuit Breakers and Fusible Cut-outs, do these comply with the requirements of the Rules Yes

Joint Boxes Section and Distribution Boards, is the construction, protection, insulation, material, and position of these as per rule Yes

single and twin ones
Cables: Single, twin, concentric, or multicore are the cables insulated and protected as per Tables IV or V of the Rules. Yes
Fall of Pressure, state maximum between bus bars and any point of the installation under maximum load 2 V.+ 3 pr. cent for lighting power
Cable Sockets and other connections, are the ends of all cables having a sectional area of 0.04 square inch and above provided with soldering sockets Yes
Paper Insulated Cables. If cables are paper covered, is the dielectric at the exposed ends of the conductor protected from moisture by being suitably sealed with insulating compound -
Cable Runs, are the cables fixed as far as possible in accessible positions not exposed to drip or accumulation of water or oil, or to high temperature from boilers, steam pipes, uptakes or other hot objects, or to avoidable risk of mechanical damage Yes
Support and Protection of Cables, state how the cables are supported and protected supported by metal clips. All power cables lead covered and armoured. Lighting cables lead covered in cabins. For the rest lead covered and steel wire plaited or armoured.
If cables are run in wood casings, are the casings and caps secured by screws Yes, are the cap screws of brass Yes, are the cables run in separate grooves No. If armoured and lead covered cables are secured by metal clips, are the clips spaced as per Table VIII Yes
Refrigerated Chambers, if lights are fitted, are the cables and fittings in accordance with the special requirements Yes
Joints in Cables, state if any, and how made, insulated, and protected No joints in main cables. Joints in section cables as pr rule.
Watertight Glands and Deck Tubes, are all cables passing through decks and watertight bulkheads provided with deck tubes or watertight glands Yes
Bushes in Beams and Non-watertight Partitions, where unarmoured cables pass through beams and non-watertight partitions, are the holes efficiently bushed Yes state the material of which the bushes are made Lead
Earthing Connections, state what earthing connections are fitted and their respective sectional areas -
are their connections made as per Rule -
Alternative Lighting, are the groups of lights in the propelling machinery space arranged as per Rule Yes
Emergency Supply, state position and method of control of the emergency supply and how the generator is driven -
Navigation Lamps, are these separately wired Yes, controlled by separate switch and separate fuses Yes, are the fuses double pole Yes, are the switches and fuses grouped in a position accessible only to the officers on watch Yes
has each navigation lamp an automatic indicator as per Rule Yes
Secondary Batteries, are they constructed and fitted as per Rule -
Fittings, are all fittings on weather decks, in stokeholds and engine rooms and wherever exposed to drip or condensed moisture, watertight Yes
are any fittings placed in spaces in which goods are liable to be stacked in close proximity to them; if so, how are they protected -
are any fittings placed in spaces where inflammable or explosive dust or gases are liable to be present, if so, how are they protected lamps contained in gastight fittings, how are the cables led in gastight tubing
where are the controlling switches situated outside of dangerous spaces
Searchlight Lamps, No. of -, whether fixed or portable -, are their fittings as per Rule -
Arc Lamps, other than searchlight lamps, No. of -, are their live parts insulated from the frame or case -, are their fittings as per Rule -
Motors, are their working parts readily accessible Yes, are the coils self-contained and readily removable for replacement Yes, are the brushes, brush holders, terminals and lubricating arrangements as per Rule Yes, are the motors placed in well-ventilated compartments in which inflammable gases cannot accumulate and clear of all inflammable material Yes
are they protected from mechanical injury and damage from water, steam or oil Yes are their axes of rotation fore and aft all exsept the turning motors.
if situated near unprotected woodwork or other combustible material, are the motors of the totally enclosed, pipe ventilated, forced draught, drip or flame proof type
, if not of this type, state distance of the combustible material horizontally or vertically above the motors - and -
Control Gear and Resistances, are the generator field and motor speed regulators, starters and controllers constructed and fitted as per Rule Yes
Lightning Conductors, where lightning conductors are required, are these fitted as per Rule Yes
Ships carrying Oil having a Flash Point less than 150° F. Have the special requirements of the Rules been complied with regarding switches, joint boxes, section and distribution boards, protection of cables, method of distribution, lead of cables, lights and fittings Yes
If portable lamps for use in dangerous spaces are supplied, are they of a type approved by the Home Office No portable lamps supported for use in dangerous spaces.

PARTICULARS OF GENERATING PLANT.									
DESCRIPTION OF GENERATOR.	No of	RATED AT				DRIVEN BY	WHERE DRIVEN BY AN INTERNAL COMBUSTION ENGINE.		
		Kilowatts.	Volts.	Ampères.	Revs. per Min.		Fuel Used.	Flash Point of Fuel.	
MAIN	2	50	110	455	400	{ 1 Dieselenine 1 Steamengine	Dieseloil	Above 150°F.	
AUXILIARY					400				
EMERGENCY									
ROTARY TRANSFORMER									

GENERATOR, LIGHTING AND HEATING CONDUCTORS.									
DESCRIPTION.	CONDUCTORS.		COMPOSITION OF STRAND.		TOTAL MAXIMUM CURRENT. AMPERES.		Approximate Length. (Lead and Return). xxx met.	Insulated with	HOW PROTECTED.
	No. per Pole.	Total Effective Area per Pole Sq. mm.	No.	Diameter.	In Circuit.	Rule.			
MAIN GENERATOR	3	285	19	2.52	455	✓	7-8	Rubber	Lead covered and steel armoured
EQUALISER CONNECTIONS	3	285	19	2.52	455	✓	7-8	"	" " "
AUXILIARY GENERATOR									
EMERGENCY GENERATOR									
ROTARY TRANSFORMER } MOTOR GENERATOR									
ENGINE ROOM... ..	1	6	7	1.05	20	✓	15	"	" " "
BOILER ROOM... ..									
AUXILIARY SWITCHBOARDS	1	10	7	1.35	36		56	"	" " "
Galley board									
Lanterns	1	4	7	0.86	2.5	✓	210	"	" " "
ACCOMMODATION aft. starb	1	6	7	1.05	22	✓	42	"	" " "
" " port	1	6	7	1.05	20	✓	50	"	" " "
" " midships	1	35	19	1.53	40	✓	180	"	" " "
" " forward	1	10	7	1.35	8	✓	100	"	" " "
Branch circuit	1	1.5	1	1.38	6	✓	-	"	" " "
WIRELESS	1	10	7	1.53	25	✓	210	"	" " "
SEARCHLIGHT									
MASTHEAD LIGHT	1	1.5	1	1.38	0.5	✓	160-100	"	" " "
SIDE LIGHTS	1	1.5	1	1.38	0.5	✓	40-40	"	" " "
COMPASS LIGHTS	1	1.5	1	1.38	0.5	✓	20	"	" " "
POOP LIGHTS	1	1.5	1	1.38	0.5	✓	210	"	" " "
CARGO LIGHTS									
ARC LAMPS									
HEATERS									

MOTOR CONDUCTORS.										
DESCRIPTION.	No. of Motors.	CONDUCTORS.		COMPOSITION OF STRAND.		TOTAL MAXIMUM CURRENT. AMPERES.		Approximate Length. (Lead and Return). xxx met.	Insulated with	HOW PROTECTED.
		No. Per Pole.	Total Effective Area per Pole Sq. mm.	No.	Diameter.	In Circuit.	Rule.			
BALLAST PUMP										
MAIN BILGE LINE PUMPS										
GENERAL SERVICE PUMP										
EMERGENCY BILGE PUMP										
SANITARY PUMP										
CIRC. SEA WATER PUMPS										
CIRC. FRESH WATER PUMPS... ..										
AIR COMPRESSOR										
FRESH WATER PUMP	2	1	4	7	0.86	23	✓	29-29	Rubber	Lead covered and steel armoured.
ENGINE TURNING GEAR... ..										
ENGINE REVERSING GEAR	2	2	190	19	2.52	310	✓	12-14	"	" "
LUBRICATING OIL PUMPS										
OIL FUEL TRANSFER PUMP										
WINDLASS										
WINCHES, FORWARD										
WINCHES, AFT										
STEERING GEAR—										
(a) MOTOR GENERATOR...										
(b) MAIN MOTOR										
WORKSHOP MOTOR	1	1	4	7	0.86	23	✓	45	"	" " "
VENTILATING FANS	2	1	2.5	1	1.78	15	✓	32-62	"	" " "
Lubr. oil separator	1	1	2.5	1	1.78	15	✓	34	"	" " "
Fuel " "	1	1	2.5	1	1.78	15	✓	34	"	" " "
Refrigerator	1	1	50	19	1.83	100	✓	31	"	" " "
Cooling water pump	1	1	2.5	1	1.78	15	✓	25	"	" " "

All Conductors are of annealed copper conforming to British Standard Specification No. 7.
The Insulated Conductors are guaranteed to withstand the immersion and resistance tests specified in the Rules.
The foregoing is a correct description.

A.-B. Götaverken

Electrical Engineers.

Date IV. 9. 31

COMPASSES.

Distance between electric generators or motors and standard compass... Wireless rotary transformer 10 met.

Distance between electric generators or motors and steering compass... Wireless rotary transformer 8 met.

The nearest cables to the compasses are as follows:—

A cable carrying Ampères feet from standard compass feet from steering compass.

A cable carrying Ampères feet from standard compass feet from steering compass.

A cable carrying Ampères feet from standard compass feet from steering compass.

Have the compasses been adjusted with and without the electric installation at work at full power.....

Has the effect of switching on and off circuits, motors and other electro-magnetic apparatus within the vicinity of the compasses been noted.....

The maximum deviation due to electric currents was found to be degrees on course in the case of the standard compass, and degrees on course in the case of the steering compass.

AKTIEBOLAGET GÖTAVEN KEN

[Signature]

Builder's Signature.

Date IV. 9. 31

Is this installation a duplicate of a previous case *No* If so, state name of vessel *✓*

General Remarks (State quality of workmanship, opinions as to class, &c.)

This electric installation has been fitted on board this vessel under my inspection and has been tested and found satisfactory.

The workmanship is good.

All the Rule requirements have been complied with.

Elec. Light

DA. 15731

Total Capacity of Generators 100 Kilowatts.

The amount of Fee ...

kr. 573.30

When applied for,

11th April 31.

When received,

6.5.31

Travelling Expenses (if any) £

[Signature]
Surveyor to Lloyd's Register of Shipping.

Committee's Minute.....

Assigned.....

Elec Lt.



© 2020

Lloyd's Register
Foundation